



CT7G

RUGGED TABLET

GET OUT THERE



Affordable, Versatile, Rugged

Now running Android 6.0 with a speedy new processor, the CT7G Rugged Tablet is ready to ramp up your data collection process in tough environments. It's got the outdoor visibility you need on a large, 7-inch display, a battery with enough juice to run all day long, and the ruggedness required to perform reliably in any environment. Not only that, but the CT7G also provides the versatility to choose from thousands of business-ready apps on the Google Play Store. All of this and more, at an affordable price that makes the CT7G an easy choice. So put down that fragile smartphone, pick up the CT7G, and get out there.



CT7G Specifications

PROCESSOR

- MediaTek MT6735 64-bit quad-core

OPERATING SYSTEM AND SOFTWARE

- Android 6.0 operating system
- Multiple languages supported



PHYSICAL

- Dimensions: 215.56 x 135.8 x 18.9 mm
- Weight: 1.3 lbs

CELL MODEM

- 4G LTE
- Most major US and EU carriers

DISPLAY

- Active viewing area: 7" (178 mm)
- High-visibility HD IPS display
- Resolution: 800 x 1280
- Portrait or landscape orientation with automatic screen rotation



CAMERA

- Front: 2 MP
- Rear: 13 MP

TOUCH SCREEN

- Projected capacitive touch screen

MEMORY

- Storage: 16 GB
- RAM: 2 GB
- Micro-SD card: up to 32G



BATTERY

- 7000 mAh Li-Ion battery

PORTS

- Micro USB (5 pin)
- 3.5 mm audio jack
- USB OTG: supports mouse & keyboard, also used for charging

KEYPAD

- Three function keys: menu, back, home
- Three side keys: two volume, power, camera, reset

RUGGEDNESS

- IP68 waterproof and dustproof
- Drop-tested to 3' onto concrete
- Operating temperature: -50 F to 122 F (-10 C to 50 C)
- Storage temperature: -104 F to 158 F (-40 C to 70 C)

SENSORS

- NFC
- E-Compass
- G-sensor
- Three-axis gyroscope
- Distance/light sensor
- Geomagnetic sensor

GPS/GNSS

- GPS + GLONASS receivers



WIRELESS CONNECTIVITY OPTIONS

- Bluetooth® 4.0 wireless technology
- Wi-Fi® IEEE 802.11 b/g/n
- Near-field communication
- FM radio
- USB disk
- Dual-SIM card slot



GET OUT THERE